

# HONDA GENERATORS

## EB5000

### Portable Gas Generator

AVAILABLE FOR RENT AT



[www.atsequipment.com](http://www.atsequipment.com)

*This generator provides up to 5000 watts of regulated power. Standard features include Steel Fuel Tank with 4-step filter, automatic voltage regulator, Auto Throttle, G.F.C.I. receptacle and 120/240V operation. Design for daily job site use, the full frame protection, standard bale hook, and 2 Wheel kit is the #1 choice of commercial users. The voltage selection switch allows for total generator output to be available through each of the 120-volt outlet for powering electric motors with large starting requirements (Output is limited to the rating of each receptacle).*



#### SPECIFICATIONS

Engine	Honda GX340
Engine, Horse Power	11 HP
Engine Type	Single cylinder, overhead valve, air-cooled
Displacement	337cc
AC Output	120/240V 5000W max. (41.7/20.8A) 4500 rated 37.5/18.8A)
Receptacles	C, E, F, H
DC Output	N/A
Starting System	Recoil
Fuel Tank Capacity	4.5 gals
Run Time per Tankful	5.7 hrs. @ rated load, 8.5 hrs. @ 1/2 load
Dimensions (L x W x H)	40.2" x 26.4" x 30.7"***
Noise Level	72 dB @ rated load
Dry Weight	197 lbs.

#### FEATURES

- Honda OHV Engine
- Oil Alert
- Electric Ignition
- Circuit breakers
- Standard wheel kit
- Automatic voltage regulator
- Full tubing frame for protection
- USDA-qualified spark arrester/muffler
- Automatic Idle
- 120/240V selector switch
- CFCI neutral bond

#### \* RECEPTACLE KEY

RECEPTACLE DESCRIPTION PLUG #

B 15A 125V Duplex\* 5-15P

C 20A 125V Duplex\* 5-15P or 5-20P

D 20A 125V GFCI Duplex\* 5-15P or 5-20P

E 20A 125V Locking Plug\* L5-20P

F 30A 125V Locking Plug\* L5-30P

G 20A 125/250V Locking Plug L14-20P

H 30A 125/250V Locking Plug L14-30P

I 50A 125/250V Locking Plug CS6365

**ATS EQUIPMENT INC. Construction Equipment & Supplies Rentals • Sales • Service**

**BOSTON MA - (800) 491-8565 (TOLL FREE)**

**CANDIA NH - (866) 491-8565 (NH/MA TOLL FREE)**