

HONDA GENERATORS

EB6500

Portable Gas Generator

AVAILABLE FOR RENT AT



www.atsequipment.com

This generator provides up to 6500 watts of commercial power. Standard features include automatic voltage regulator, Auto Throttle, G.F.C.I. receptacle and 120/240V operation. This unit also comes standard with a 2-wheel Transport Kit. The voltage selection switch allows for total generator output to be available through each of the 120 volt outlet for powering electric motors with large starting requirements (Output is limited to the rating of each receptacle).



SPECIFICATIONS

Engine	Honda GX390
Engine, Horse Power	13 HP
Engine Type	Single cylinder, overhead valve, air-cooled
Displacement	389cc
AC Output	120/240V 6500W max. (54.1/27.1A) 5500W rated (45.8/22.9A)
Receptacles	C, E, F, H
DC Output	N/A
Starting System	Recoil
Fuel Tank Capacity	4.5 gals
Run Time per Tankful	5.3 hrs. @ rated load, 8.1 hrs. @ 1/2 load
Dimensions (L x W x H)	47.2" x 26.2" x 28.3"***
Noise Level	78 dB @ rated load
Dry Weight	217 lbs.

FEATURES

- Honda OHV Engine
- Oil Alert
- Electric Ignition
- Circuit breakers
- Standard wheel kit
- Automatic voltage regulator
- Full tubing frame for protection
- USDA-qualified spark arrester/muffler
- Automatic Idle
- 120/240V selector switch
- CFCI neutral bond

* RECEPTACLE KEY

RECEPTACLE DESCRIPTION PLUG #

B 15A 125V Duplex™ 5-15P

C 20A 125V Duplex™ 5-15P or 5-20P

D 20A 125V GFCI Duplex™ 5-15P or 5-20P

E 20A 125V Locking Plug™ L5-20P

F 30A 125V Locking Plug™ L5-30P

G 20A 125/250V Locking Plug L14-20P

H 30A 125/250V Locking Plug L14-30P

I 50A 125/250V Locking Plug CS6365

ATS EQUIPMENT INC.

Construction Equipment & Supplies

Rentals • Sales • Service

**BOSTON, MA
(617) 825-3600**

**AUBURN, MA
(508) 832-8500**

**CANDIA, NH
(603) 483-2100**